

A. Introduction

1. **Title:** Real Power Balancing Control Performance
2. **Number:** BAL-001-0.1a
3. **Purpose:** To maintain Interconnection steady-state frequency within defined limits by balancing real power demand and supply in real-time.
4. **Applicability:**
 - 4.1. Balancing Authorities
5. **Effective Date:** May 13, 2009

B. Requirements

- R1.** Each Balancing Authority shall operate such that, on a rolling 12-month basis, the average of the clock-minute averages of the Balancing Authority's Area Control Error (ACE) divided by 10B (B is the clock-minute average of the Balancing Authority Area's Frequency Bias) times the corresponding clock-minute averages of the Interconnection's Frequency Error is less than a specific limit. This limit ϵ_1^2 is a constant derived from a targeted frequency bound (separately calculated for each Interconnection) that is reviewed and set as necessary by the NERC Operating Committee.

$$AVG_{Period} \left[\left(\frac{ACE_i}{-10B_i} \right)_1 * \Delta F_1 \right] \leq \epsilon_1^2 \text{ or } \frac{AVG_{Period} \left[\left(\frac{ACE_i}{-10B_i} \right)_1 * \Delta F_1 \right]}{\epsilon_1^2} \leq 1$$

The equation for ACE is:

$$ACE = (NI_A - NI_S) - 10B (F_A - F_S) - I_{ME}$$

where:

- NI_A is the algebraic sum of actual flows on all tie lines.
 - NI_S is the algebraic sum of scheduled flows on all tie lines.
 - B is the Frequency Bias Setting (MW/0.1 Hz) for the Balancing Authority. The constant factor 10 converts the frequency setting to MW/Hz.
 - F_A is the actual frequency.
 - F_S is the scheduled frequency. F_S is normally 60 Hz but may be offset to effect manual time error corrections.
 - I_{ME} is the meter error correction factor typically estimated from the difference between the integrated hourly average of the net tie line flows (NI_A) and the hourly net interchange demand measurement (megawatt-hour). This term should normally be very small or zero.
- R2.** Each Balancing Authority shall operate such that its average ACE for at least 90% of clock-ten-minute periods (6 non-overlapping periods per hour) during a calendar month is within a specific limit, referred to as L_{10} .

$$AVG_{10\text{-minute}} (ACE_i) \leq L_{10}$$

where:

$$L_{10} = 1.65 \epsilon_{10} \sqrt{(-10B_i)(-10B_s)}$$

ϵ_{10} is a constant derived from the targeted frequency bound. It is the targeted root-mean-square (RMS) value of ten-minute average Frequency Error based on frequency performance over a given year. The bound, ϵ_{10} , is the same for every Balancing Authority Area within an Interconnection, and B_s is the sum of the Frequency Bias Settings of the Balancing Authority Areas in the respective Interconnection. For Balancing Authority Areas with variable bias, this is equal to the sum of the minimum Frequency Bias Settings.

- R3.** Each Balancing Authority providing Overlap Regulation Service shall evaluate Requirement R1 (i.e., Control Performance Standard 1 or CPS1) and Requirement R2 (i.e., Control Performance Standard 2 or CPS2) using the characteristics of the combined ACE and combined Frequency Bias Settings.
- R4.** Any Balancing Authority receiving Overlap Regulation Service shall not have its control performance evaluated (i.e. from a control performance perspective, the Balancing Authority has shifted all control requirements to the Balancing Authority providing Overlap Regulation Service).

C. Measures

- M1.** Each Balancing Authority shall achieve, as a minimum, Requirement 1 (CPS1) compliance of 100%.

CPS1 is calculated by converting a compliance ratio to a compliance percentage as follows:

$$CPS1 = (2 - CF) * 100\%$$

The frequency-related compliance factor, CF, is a ratio of all one-minute compliance parameters accumulated over 12 months divided by the target frequency bound:

$$CF = \frac{CF_{12\text{-month}}}{(\epsilon_1)^2}$$

where: ϵ_1 is defined in Requirement R1.

The rating index $CF_{12\text{-month}}$ is derived from 12 months of data. The basic unit of data comes from one-minute averages of ACE, Frequency Error and Frequency Bias Settings.

A clock-minute average is the average of the reporting Balancing Authority's valid measured variable (i.e., for ACE and for Frequency Error) for each sampling cycle during a given clock-minute.

$$\left(\frac{ACE}{-10B} \right)_{\text{clock-minute}} = \frac{\left(\frac{\sum ACE_{\text{sampling cycles in clock-minute}}}{n_{\text{sampling cycles in clock-minute}}} \right)}{-10B}$$

$$\Delta F_{\text{clock-minute}} = \frac{\sum \Delta F_{\text{sampling cycles in clock-minute}}}{n_{\text{sampling cycles in clock-minute}}}$$

The Balancing Authority's clock-minute compliance factor (CF) becomes:

$$CF_{\text{clock-minute}} = \left[\left(\frac{ACE}{-10B} \right)_{\text{clock-minute}} * \Delta F_{\text{clock-minute}} \right]$$

Normally, sixty (60) clock-minute averages of the reporting Balancing Authority's ACE and of the respective Interconnection's Frequency Error will be used to compute the respective hourly average compliance parameter.

$$CF_{\text{clock-hour}} = \frac{\sum CF_{\text{clock-minute}}}{n_{\text{clock-minute samples in hour}}}$$

The reporting Balancing Authority shall be able to recalculate and store each of the respective clock-hour averages (CF clock-hour average-month) as well as the respective number of samples for each of the twenty-four (24) hours (one for each clock-hour, i.e., hour-ending (HE) 0100, HE 0200, ..., HE 2400).

$$CF_{\text{clock-hour average-month}} = \frac{\sum_{\text{days-in-month}} [(CF_{\text{clock-hour}})(n_{\text{one-minute samples in clock-hour}})]}{\sum_{\text{days-in month}} [n_{\text{one-minute samples in clock-hour}}]}$$

$$CF_{\text{month}} = \frac{\sum_{\text{hours-in-day}} [(CF_{\text{clock-hour average-month}})(n_{\text{one-minute samples in clock-hour averages}})]}{\sum_{\text{hours-in day}} [n_{\text{one-minute samples in clock-hour averages}}]}$$

The 12-month compliance factor becomes:

$$CF_{12\text{-month}} = \frac{\sum_{i=1}^{12} (CF_{\text{month-}i})(n_{(\text{one-minute samples in month})-i})}{\sum_{i=1}^{12} [n_{(\text{one-minute samples in month})-i}]}$$

In order to ensure that the average ACE and Frequency Deviation calculated for any one-minute interval is representative of that one-minute interval, it is necessary that at least 50% of both ACE and Frequency Deviation samples during that one-minute interval be present. Should a sustained interruption in the recording of ACE or Frequency Deviation due to loss of telemetering or computer unavailability result in a one-minute interval not containing at least 50% of samples of both ACE and Frequency Deviation, that one-minute interval shall be excluded from the calculation of CPS1.

- M2.** Each Balancing Authority shall achieve, as a minimum, Requirement R2 (CPS2) compliance of 90%. CPS2 relates to a bound on the ten-minute average of ACE. A compliance percentage is calculated as follows:

$$CPS2 = \left[1 - \frac{\text{Violations}_{\text{month}}}{(\text{Total Periods}_{\text{month}} - \text{Unavailable Periods}_{\text{month}})} \right] * 100$$

The violations per month are a count of the number of periods that ACE clock-ten-minutes exceeded L_{10} . ACE clock-ten-minutes is the sum of valid ACE samples within a clock-ten-minute period divided by the number of valid samples.

Violation clock-ten-minutes

$$= 0 \text{ if } \left| \frac{\sum ACE}{n_{\text{samples in 10-minutes}}} \right| \leq L_{10}$$

$$= 1 \text{ if } \left| \frac{\sum ACE}{n_{\text{samples in 10-minutes}}} \right| > L_{10}$$

Each Balancing Authority shall report the total number of violations and unavailable periods for the month. L_{10} is defined in Requirement R2.

Since CPS2 requires that ACE be averaged over a discrete time period, the same factors that limit total periods per month will limit violations per month. The calculation of total periods per month and violations per month, therefore, must be discussed jointly.

A condition may arise which may impact the normal calculation of total periods per month and violations per month. This condition is a sustained interruption in the recording of ACE.

In order to ensure that the average ACE calculated for any ten-minute interval is representative of that ten-minute interval, it is necessary that at least half the ACE data samples are present for that interval. Should half or more of the ACE data be unavailable due to loss of telemetering or computer unavailability, that ten-minute interval shall be omitted from the calculation of CPS2.

D. Compliance

1. Compliance Monitoring Process

1.1. Compliance Monitoring Responsibility

Regional Reliability Organization.

1.2. Compliance Monitoring Period and Reset Timeframe

One calendar month.

1.3. Data Retention

The data that supports the calculation of CPS1 and CPS2 (Appendix 1-BAL-001-0) are to be retained in electronic form for at least a one-year period. If the CPS1 and CPS2 data for a Balancing Authority Area are undergoing a review to address a question that has been raised regarding the data, the data are to be saved beyond the normal retention period until the question is formally resolved. Each Balancing Authority shall retain for a rolling 12-month period the values of: one-minute average ACE (ACE_i), one-minute average Frequency Error, and, if using variable bias, one-minute average Frequency Bias.

1.4. Additional Compliance Information

None.

2. Levels of Non-Compliance – CPS1

2.1. Level 1: The Balancing Authority Area's value of CPS1 is less than 100% but greater than or equal to 95%.

2.2. Level 2: The Balancing Authority Area's value of CPS1 is less than 95% but greater than or equal to 90%.

2.3. Level 3: The Balancing Authority Area’s value of CPS1 is less than 90% but greater than or equal to 85%.

2.4. Level 4: The Balancing Authority Area’s value of CPS1 is less than 85%.

3. Levels of Non-Compliance – CPS2

3.1. Level 1: The Balancing Authority Area’s value of CPS2 is less than 90% but greater than or equal to 85%.

3.2. Level 2: The Balancing Authority Area’s value of CPS2 is less than 85% but greater than or equal to 80%.

3.3. Level 3: The Balancing Authority Area’s value of CPS2 is less than 80% but greater than or equal to 75%.

3.4. Level 4: The Balancing Authority Area’s value of CPS2 is less than 75%.

E. Regional Differences

1. The [ERCOT Control Performance Standard 2 Waiver](#) approved November 21, 2002.

F. Associated Documents

1. Appendix 2 — Interpretation of Requirement R1 (October 23, 2007).

Version History

Version	Date	Action	Change Tracking
0	February 8, 2005	BOT Approval	New
0	April 1, 2005	Effective Implementation Date	New
0	August 8, 2005	Removed “Proposed” from Effective Date	Errata
0	July 24, 2007	Corrected R3 to reference M1 and M2 instead of R1 and R2	Errata
0a	December 19, 2007	Added Appendix 2 – Interpretation of R1 approved by BOT on October 23, 2007	Revised
0a	January 16, 2008	In Section A.2., Added “a” to end of standard number In Section F, corrected automatic numbering from “2” to “1” and removed “approved” and added parenthesis to “(October 23, 2007)”	Errata
0	January 23, 2008	Reversed errata change from July 24, 2007	Errata
0.1a	October 29, 2008	Board approved errata changes; updated version number to “0.1a”	Errata
0.1a	May 13, 2009	Approved by FERC	

Appendix 1-BAL-001-0 CPS1 and CPS2 Data

CPS1 DATA	Description	Retention Requirements
ε_1	A constant derived from the targeted frequency bound. This number is the same for each Balancing Authority Area in the Interconnection.	Retain the value of ε_1 used in CPS1 calculation.
ACE_i	The clock-minute average of ACE.	Retain the 1-minute average values of ACE (525,600 values).
B_i	The Frequency Bias of the Balancing Authority Area.	Retain the value(s) of B_i used in the CPS1 calculation.
F_A	The actual measured frequency.	Retain the 1-minute average frequency values (525,600 values).
F_S	Scheduled frequency for the Interconnection.	Retain the 1-minute average frequency values (525,600 values).

CPS2 DATA	Description	Retention Requirements
V	Number of incidents per hour in which the absolute value of ACE clock-ten-minutes is greater than L_{10} .	Retain the values of V used in CPS2 calculation.
ε_{10}	A constant derived from the frequency bound. It is the same for each Balancing Authority Area within an Interconnection.	Retain the value of ε_{10} used in CPS2 calculation.
B_i	The Frequency Bias of the Balancing Authority Area.	Retain the value of B_i used in the CPS2 calculation.
B_s	The sum of Frequency Bias of the Balancing Authority Areas in the respective Interconnection. For systems with variable bias, this is equal to the sum of the minimum Frequency Bias Setting.	Retain the value of B_s used in the CPS2 calculation. Retain the 1-minute minimum bias value (525,600 values).
U	Number of unavailable ten-minute periods per hour used in calculating CPS2.	Retain the number of 10-minute unavailable periods used in calculating CPS2 for the reporting period.

Appendix 2

Interpretation of Requirement 1

Request: *Does the WECC Automatic Time Error Control Procedure (WATEC) violate Requirement 1 of BAL-001-0?*

Interpretation:

Requirement 1 of BAL-001 — Real Power Balancing Control Performance, is the definition of the area control error (ACE) equation and the limits established for Control Performance Standard 1 (CPS1).

BAL-001-0

R1. Each Balancing Authority shall operate such that, on a rolling 12-month basis, the average of the clock-minute averages of the Balancing Authority's Area Control Error (ACE) divided by 10B (B is the clock-minute average of the Balancing Authority Area's Frequency Bias) times the corresponding clock-minute averages of the Interconnection's Frequency Error is less than a specific limit. This limit ϵ_{12} is a constant derived from a targeted frequency bound (separately calculated for each Interconnection) that is reviewed and set as necessary by the NERC Operating Committee.

- The WATEC procedural documents ask Balancing Authorities to maintain raw ACE for CPS reporting and to control via WATEC-adjusted ACE.
- As long as Balancing Authorities use raw (unadjusted for WATEC) ACE for CPS reporting purposes, the use of WATEC for control is not in violation of BAL-001 Requirement 1.

Standard BAL-001-0.1a — Real Power Balancing Control Performance

Appendix QC-BAL-001-0.1a Provisions specific to the standard BAL-001-0.1a applicable in Québec

This appendix establishes specific provisions for the application of the standard in Québec. Provisions of the standard and of its appendix must be read together for the purposes of understanding and interpretation. Where the standard and appendix differ, the appendix shall prevail.

A. Introduction

1. **Title:** Real Power Balancing Control Performance
2. **Number:** BAL-001-0.1a
3. **Purpose:** No specific provision
4. **Applicability:** No specific provision
5. **Effective Date:**
 - 5.1. Adoption of the standard by the Régie de l'énergie: December 19, 2014
 - 5.2. Adoption of the appendix by the Régie de l'énergie: December 19, 2014
 - 5.3. Effective date of the standard and its appendix in Québec: April 1, 2015

B. Requirements

No specific provision

C. Measures

No specific provision

D. Compliance

1. Compliance Monitoring Process

1.1. Compliance Monitoring Responsibility

The Régie de l'énergie is responsible, in Québec, for compliance monitoring with respect to the reliability standard and its appendix that it adopts.

1.2. Compliance Monitoring Period and Reset Timeframe

No specific provision

1.3. Data Retention

No specific provision

1.4. Additional Compliance Information

No specific provision

2. Levels of Non-Compliance – CPS1

No specific provision

3. Levels of Non-Compliance – CPS2

No specific provision

E. Regional Differences

No specific provision

Standard BAL-001-0.1a — Real Power Balancing Control Performance

Appendix QC-BAL-001-0.1a
Provisions specific to the standard BAL-001-0.1a applicable in Québec

F. Associated Documents

No specific provision

Appendix 1 – BAL-001-0

No specific provision

Appendix 2

No specific provision

Revision History

Revision	Adoption Date	Action	Change Tracking
0	December 19, 2014	New appendix	New