

## A. Introduction

1. **Title: Operational Reliability Data**
2. **Number: TOP-003-3**
3. **Purpose:** To ensure that the Transmission Operator and Balancing Authority have data needed to fulfill their operational and planning responsibilities.
4. **Applicability:**
  - 4.1. Transmission Operator
  - 4.2. Balancing Authority
  - 4.3. Generator Owner
  - 4.4. Generator Operator
  - 4.5. Load-Serving Entity
  - 4.6. Transmission Owner
  - 4.7. Distribution Provider
5. **Effective Date:**

See Implementation Plan.
6. **Background:**

See Project 2014-03 [project page](#).

## B. Requirements and Measures

- R1. Each Transmission Operator shall maintain a documented specification for the data necessary for it to perform its Operational Planning Analyses, Real-time monitoring, and Real-time Assessments. The data specification shall include, but not be limited to: *[Violation Risk Factor: Low] [Time Horizon: Operations Planning]*
  - 1.1. A list of data and information needed by the Transmission Operator to support its Operational Planning Analyses, Real-time monitoring, and Real-time Assessments including non-BES data and external network data as deemed necessary by the Transmission Operator.
  - 1.2. Provisions for notification of current Protection System and Special Protection System status or degradation that impacts System reliability.
  - 1.3. A periodicity for providing data.
  - 1.4. The deadline by which the respondent is to provide the indicated data.
- M1. Each Transmission Operator shall make available its dated, current, in force documented specification for data.

- R2.** Each Balancing Authority shall maintain a documented specification for the data necessary for it to perform its analysis functions and Real-time monitoring. The data specification shall include, but not be limited to: *[Violation Risk Factor: Low] [Time Horizon: Operations Planning]*
- 2.1.** A list of data and information needed by the Balancing Authority to support its analysis functions and Real-time monitoring.
  - 2.2.** Provisions for notification of current Protection System and Special Protection System status or degradation that impacts System reliability.
  - 2.3.** A periodicity for providing data.
  - 2.4.** The deadline by which the respondent is to provide the indicated data.
- M2.** Each Balancing Authority shall make available its dated, current, in force documented specification for data.
- R3.** Each Transmission Operator shall distribute its data specification to entities that have data required by the Transmission Operator’s Operational Planning Analyses, Real-time monitoring, and Real-time Assessment. *[Violation Risk Factor: Low] [Time Horizon: Operations Planning]*
- M3.** Each Transmission Operator shall make available evidence that it has distributed its data specification to entities that have data required by the Transmission Operator’s Operational Planning Analyses, Real-time monitoring, and Real-time Assessments. Such evidence could include but is not limited to web postings with an electronic notice of the posting, dated operator logs, voice recordings, postal receipts showing the recipient, date and contents, or e-mail records.
- R4.** Each Balancing Authority shall distribute its data specification to entities that have data required by the Balancing Authority’s analysis functions and Real-time monitoring. *[Violation Risk Factor: Low] [Time Horizon: Operations Planning]*
- M4.** Each Balancing Authority shall make available evidence that it has distributed its data specification to entities that have data required by the Balancing Authority’s analysis functions and Real-time monitoring. Such evidence could include but is not limited to web postings with an electronic notice of the posting, dated operator logs, voice recordings, postal receipts showing the recipient, or e-mail records.
- R5.** Each Transmission Operator, Balancing Authority, Generator Owner, Generator Operator, Load-Serving Entity, Transmission Owner, and Distribution Provider receiving a data specification in Requirement R3 or R4 shall satisfy the obligations of the documented specifications using: *[Violation Risk Factor: Medium] [Time Horizon: Operations Planning, Same-Day Operations, Real-time Operations]*
- 5.1.** A mutually agreeable format
  - 5.2.** A mutually agreeable process for resolving data conflicts
  - 5.3.** A mutually agreeable security protocol

- M5.** Each Transmission Operator, Balancing Authority, Generator Owner, Generator Operator, Load-Serving Entity, Transmission Owner, and Distribution Provider receiving a data specification in Requirement R3 or R4 shall make available evidence that it has satisfied the obligations of the documented specifications. Such evidence could include, but is not limited to, electronic or hard copies of data transmittals or attestations of receiving entities.

## **C. Compliance**

### **1. Compliance Monitoring Process**

#### **1.1. Compliance Monitoring Process**

As defined in the NERC Rules of Procedure, “Compliance Enforcement Authority” (CEA) means NERC or the Regional Entity in their respective roles of monitoring and enforcing compliance with the NERC Reliability Standards.

#### **1.2. Compliance Monitoring and Assessment Processes**

As defined in the NERC Rules of Procedure, “Compliance Monitoring and Assessment Processes” refers to the identification of the processes that will be used to evaluate data or information for the purpose of assessing performance or outcomes with the associated reliability standard.

#### **1.3. Data Retention**

The following evidence retention periods identify the period of time an entity is required to retain specific evidence to demonstrate compliance. For instances where the evidence retention period specified below is shorter than the time since the last audit, the Compliance Enforcement Authority may ask an entity to provide other evidence to show that it was compliant for the full time period since the last audit.

Each responsible entity shall keep data or evidence to show compliance as identified below unless directed by its Compliance Enforcement Authority to retain specific evidence for a longer period of time as part of an investigation:

Each Transmission Operator shall retain its dated, current, in force, documented specification for the data necessary for it to perform its Operational Planning Analyses, Real-time monitoring, and Real-time Assessments in accordance with Requirement R1 and Measurement M1 as well as any documents in force since the last compliance audit.

Each Balancing Authority shall retain its dated, current, in force, documented specification for the data necessary for it to perform its analysis functions and Real-time monitoring in accordance with Requirement R2 and Measurement M2 as well as any documents in force since the last compliance audit.

Each Transmission Operator shall retain evidence for three calendar years that it has distributed its data specification to entities that have data required by the

Transmission Operator's Operational Planning Analyses, Real-time monitoring, and Real-time Assessments in accordance with Requirement R3 and Measurement M3.

Each Balancing Authority shall retain evidence for three calendar years that it has distributed its data specification to entities that have data required by the Balancing Authority's analysis functions and Real-time monitoring in accordance with Requirement R4 and Measurement M4.

Each Balancing Authority, Generator Owner, Generator Operator, Load-Serving Entity, Transmission Operator, Transmission Owner, and Distribution Provider receiving a data specification in Requirement R3 or R4 shall retain evidence for the most recent 90-calendar days that it has satisfied the obligations of the documented specifications in accordance with Requirement R5 and Measurement M5.

If a responsible entity is found non-compliant, it shall keep information related to the non-compliance until mitigation is complete and approved or the time period specified above, whichever is longer.

The Compliance Enforcement Authority shall keep the last audit records and all requested and submitted subsequent audit records.

**1.4. Additional Compliance Information**

None.

Table of Compliance Elements

R #	Time Horizon	VRF	Violation Severity Levels			
			Lower VSL	Moderate VSL	High VSL	Severe VSL
R1	Operations Planning	Low	The Transmission Operator did not include one of the parts (Part 1.1 through Part 1.4) of the documented specification for the data necessary for it to perform its Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.	The Transmission Operator did not include two of the parts (Part 1.1 through Part 1.4) of the documented specification for the data necessary for it to perform its Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.	The Transmission Operator did not include three of the parts (Part 1.1 through Part 1.4) of the documented specification for the data necessary for it to perform its Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.	The Transmission Operator did not include four of the parts (Part 1.1 through Part 1.4) of the documented specification for the data necessary for it to perform its Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.  OR, The Transmission Operator did not have a documented specification for the data necessary for it to perform its Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.

**Standard TOP-003-3 — Operational Reliability Data**

R #	Time Horizon	VRF	Violation Severity Levels			
			Lower VSL	Moderate VSL	High VSL	Severe VSL
R2	Operations Planning	Low	The Balancing Authority did not include one of the parts (Part 2.1 through Part 2.4) of the documented specification for the data necessary for it to perform its analysis functions and Real-time monitoring.	The Balancing Authority did not include two of the parts (Part 2.1 through Part 2.4) of the documented specification for the data necessary for it to perform its analysis functions and Real-time monitoring.	The Balancing Authority did not include three of the parts (Part 2.1 through Part 2.4) of the documented specification for the data necessary for it to perform its analysis functions and Real-time monitoring.	The Balancing Authority did not include four of the parts (Part 2.1 through Part 2.4) of the documented specification for the data necessary for it to perform its analysis functions and Real-time monitoring.  OR,  The Balancing Authority did not have a documented specification for the data necessary for it to perform its analysis functions and Real-time monitoring.
<p>For the Requirement R3 and R4 VSLs only, the intent of the SDT is to start with the Severe VSL first and then to work your way to the left until you find the situation that fits. In this manner, the VSL will not be discriminatory by size of entity. If a small entity has just one affected reliability entity to inform, the intent is that that situation would be a Severe violation.</p>						
R3	Operations Planning	Low	The Transmission Operator did not distribute its data	The Transmission Operator did not distribute its data	The Transmission Operator did not distribute its data	The Transmission Operator did not distribute its data

**Standard TOP-003-3 — Operational Reliability Data**

R #	Time Horizon	VRF	Violation Severity Levels			
			Lower VSL	Moderate VSL	High VSL	Severe VSL
			specification to one entity, or 5% or less of the entities, whichever is greater, that have data required by the Transmission Operator's Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.	specification to two entities, or more than 5% and less than or equal to 10% of the reliability entities, whichever is greater, that have data required by the Transmission Operator's Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.	specification to three entities, or more than 10% and less than or equal to 15% of the reliability entities, whichever is greater, that have data required by the Transmission Operator's Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.	specification to four or more entities, or more than 15% of the entities that have data required by the Transmission Operator's Operational Planning Analyses, Real-time monitoring, and Real-time Assessments.
R4	Operations Planning	Low	The Balancing Authority did not distribute its data specification to one entity, or 5% or less of the entities, whichever is greater, that have data required by the Balancing Authority's analysis functions and Real-time monitoring.	The Balancing Authority did not distribute its data specification to two entities, or more than 5% and less than or equal to 10% of the entities, whichever is greater, that have data required by the Balancing Authority's analysis functions and Real-time monitoring.	The Balancing Authority did not distribute its data specification to three entities, or more than 10% and less than or equal to 15% of the entities, whichever is greater, that have data required by the Balancing Authority's analysis functions and Real-time monitoring.	The Balancing Authority did not distribute its data specification to four or more entities, or more than 15% of the entities that have data required by the Balancing Authority's analysis functions and Real-time monitoring.

**Standard TOP-003-3 — Operational Reliability Data**

R #	Time Horizon	VRF	Violation Severity Levels			
			Lower VSL	Moderate VSL	High VSL	Severe VSL
R5	Operations Planning, Same-Day Operations, Real-time Operations	Medium	The responsible entity receiving a data specification in Requirement R3 or R4 satisfied the obligations in the data specification but did not meet one of the criteria shown in Requirement R5 (Parts 5.1 – 5.3).	The responsible entity receiving a data specification in Requirement R3 or R4 satisfied the obligations in the data specification but did not meet two of the criteria shown in Requirement R5 (Parts 5.1 – 5.3).	The responsible entity receiving a data specification in Requirement R3 or R4 satisfied the obligations in the data specification but did not meet three of the criteria shown in Requirement R5 (Parts 5.1 – 5.3).	The responsible entity receiving a data specification in Requirement R3 or R4 did not satisfy the obligations of the documented specifications for data.



**D. Regional Variances**

None.

**E. Interpretations**

None.

**F. Associated Documents**

None.

**Version History**

Version	Date	Action	Change Tracking
0	April 1, 2005	Effective Date	New
0	August 8, 2005	Removed "Proposed" from Effective Date	Errata
1		Modified R1.2 Modified M1 Replaced Levels of Non-compliance with the Feb 28, BOT approved Violation Severity Levels (VSLs)	Revised
1	October 17, 2008	Adopted by NERC Board of Trustees	
1	March 17, 2011	Order issued by FERC approving TOP-003-1 (approval effective 5/23/11)	
2	May 6, 2012	Revised under Project 2007-03	Revised
2	May 9, 2012	Adopted by Board of Trustees	Revised
3	April 2014	Changes pursuant to Project 2014-03	Revised
3	November 13, 2014	Adopted by Board of Trustees	Revisions under Project 2014-03

### Guidelines and Technical Basis

#### **Rationale:**

During development of this standard, text boxes were embedded within the standard to explain the rationale for various parts of the standard. Upon BOT approval, the text from the rationale text boxes was moved to this section.

#### **Rationale for Definitions:**

Changes made to the proposed definitions were made in order to respond to issues raised in NOPR paragraphs 55, 73, and 74 dealing with analysis of SOLs in all time horizons, questions on Protection Systems and Special Protection Systems in NOPR paragraph 78, and recommendations on phase angles from the SW Outage Report (recommendation 27). The intent of such changes is to ensure that Real-time Assessments contain sufficient details to result in an appropriate level of situational awareness. Some examples include: 1) analyzing phase angles which may result in the implementation of an Operating Plan to adjust generation or curtail transactions so that a Transmission facility may be returned to service, or 2) evaluating the impact of a modified Contingency resulting from the status change of a Special Protection Scheme from enabled/in-service to disabled/out-of-service.

#### **Rationale for R1:**

Changes to proposed Requirement R1, Part 1.1 are in response to issues raised in NOPR paragraph 67 on the need for obtaining non-BES and external network data necessary for the Transmission Operator to fulfill its responsibilities.

Proposed Requirement R1, Part 1.2 is in response to NOPR paragraph 78 on relay data. The language has been moved from approved PRC-001-1.

Corresponding changes have been made to Requirement R2 for the Balancing Authority and to proposed IRO-010-2, Requirement R1 for the Reliability Coordinator.

#### **Rationale for R5:**

Proposed Requirement R5, Part 5.3 is in response to NOPR paragraph 92 where concerns were raised about data exchange through secured networks.

## Standard TOP-003-3 — Operational Reliability Data

### Appendix QC-TOP-003-3 Provisions specific to the standard TOP-003-3 applicable in Québec

---

This appendix establishes specific provisions for the application of the standard in Québec. Provisions of the standard and of its appendix must be read together for the purposes of understanding and interpretation. Where the standard and appendix differ, the appendix shall prevail.

#### A. Introduction

1. **Title:** Operational Reliability Data

2. **Number:** TOP-003-3

3. **Purpose:** No specific provision

4. **Applicability:**

##### Functions

No specific provision

##### Facilities

This standard only applies to the facilities of the Main Transmission System (RTP).

5. **Effective Date:**

5.1. Adoption of the standard by the Régie de l'énergie: June 16, 2017

5.2. Adoption of the appendix by the Régie de l'énergie: June 16, 2017

5.3. Effective date of the standard and its appendix in Québec: July 1<sup>st</sup> 2017

6. **Background :**

No specific provision

#### B. Requirements and Measures

##### Specific provisions applicable to requirement R1 (1.1):

The Transmission Operator does not have to include non-RTP data it deems necessary in the data specification.

##### Specific provisions applicable to requirement R5 :

The Generator Operator for industrial use must provide to the Transmission Operator and the Balancing Authority data related to :

(i) the net power at the connection points of its system in the planning and real time horizon ;

(ii) the total production of its generation facilities and its system load in the planning time horizon.

If the Generator Operator for industrial use receives a data specification document distributed in accordance with requirement R3 or R4, it is only required to comply with the provisions relating to the data to be provided.

#### C. Compliance

1. **Compliance Monitoring Process**

##### 1.1. Compliance Monitoring Process

The Régie de l'énergie is responsible, in Québec, for compliance monitoring with respect to the reliability standard and its appendix that it adopts.

##### 1.2. Compliance Monitoring and Assessment Processes

Compliance Audit

## Standard TOP-003-3 — Operational Reliability Data

### Appendix QC-TOP-003-3 Provisions specific to the standard TOP-003-3 applicable in Québec

---

Self-Certification

Spot Check

Compliance Investigation

Non-Compliance Self-Reporting

Periodic Data Submittal

Exception Reporting

Investigation following a complaint

#### **1.3. Data Retention**

No specific provision

#### **1.4. Additional Compliance Information**

No specific provision

#### **2. Table of Compliance Elements**

No specific provision

#### **D. Regional Variances**

No specific provision

#### **E. Interpretations**

No specific provision

#### **F. Associated Documents**

No specific provision

#### **Guidelines and Technical Basis**

No specific provision

#### **Revision History**

<b>Revision</b>	<b>Date</b>	<b>Action</b>	<b>Change Tracking</b>
0	June 16, 2017	New appendix	New